

Quick Start Guide



THE ULTIMATE TIME MACHINE
..... For Complete Control



Certificate No.:SAA192515EA



Change
Begins
Here

Important - To ensure trouble free operation, please charge up your new Time-R in a wall socket for a minimum of two hours before use.

To Set The Clock

▲ or ▼
To Adjust Time

◀ or ▶
To Scroll

Confirm

Input current time
e.g. 06:00:00pm

Press for 3 secs until the numbers flash.
Clock

SWITCH 12/24 HRS

Confirm
+▲

Press and hold CONFIRM, then press up arrow to choose AM/PM for 12hrs or blank for 24hrs

TIMED MODE - up to 15 settings

ON 00:--:--

OFF 00:--:--

Scroll to TIMED Mode

▲ or ▼
To Adjust Time

◀ or ▶
To Scroll

Confirm
or
For Next Group Setting

Confirm
Once you have finished all groups setting

Input On & OFF Time for Group 1
e.g. 6:30am - 12:00pm

Mode

TIMED MODE - Display shown after programming

ON 06:30:00 AM Next On Time

OFF 12:00:00 PM Next OFF Time

ON 06:00:00 AM Current Time

OFF 06:35:00 AM Starts Counting On Time

e.g. current time is 6:00am

e.g. current time is 6:35am

Option: To Lock, Press Confirm 3 Times After Finished Setting

REPEAT MODE - from min 1 sec, up to 99hrs setting

ON H M S

OFF H M S

Scroll to REPEAT Mode

▲ or ▼
To Adjust Time

◀ or ▶
To Scroll

Confirm

Input Repeat Cycle
e.g. 15 secs ON for every 1 hour

Mode

REPEAT MODE - Display Shown After Programming

ON 00:00:15 Starts Counting ON Time

OFF 00:59:45 Starts Counting OFF Time

After 15 Secs ON

Option: To Lock, Press Confirm 3 Times After Finished Setting

COMBINED MODE - Up To 3 Group Settings

ON 00:00:00
OFF ---:---:---
Group 1
COMBINED

▲ or ▼
To Adjust Time

◀ or ▶
To Scroll

ON 06:00:00 AM
OFF 12:00:00 PM
COMBINED

e.g. 6:00am - 12:00pm
15secs on every 1 hr.

For Group 1
Cycle Setting

COMBINED MODE -
Display Shown After
Programming

ON 06:00:00 AM
OFF ---:---:---
COMBINED

Next On Time

ON 05:30:00 AM
OFF ---:---:---
COMBINED

Current Time

e.g. Current Time Is 5:30am

ON 00:00:15
OFF 00:59:45
COMBINED

Starts Counting
ON time,
then OFF
time

When It Is 6:00am

Option: To Lock, Press Confirm 3 Times After Finished Setting

MANUAL ON and OFF MODE

Manual OFF:
press CLOCK
5 times

Manual ON:
press CLEAR
5 times

What is Lock Function?

To prevent accidental adjustment, there is a lock option. To lock, press CONFIRM 3 times after finished setting. It only freezes the MODE button, other buttons will still function. To unlock, press CONFIRM 3 times



L to Indicate It's Locked

HOW TO CHECK:

When TIME-R is in operation, press CHECK once, then press right arrow to move to the page of each setting. Press CHECK again to return to current operation

HOW TO CLEAR:

1. During setting, press CLEAR once to erase the whole page, dashes appear

2. Press CONFIRM to erase the setting or CLEAR again to return to the previous setting

HOW TO CHECK CURRENT TIME:

During operation, press CLOCK once to check current time

PRECAUTIONS:

1. Please always keep the timer indoors and in dry place whether it's in operation or not
2. Do not use with power extension cords
3. Always operate the timer with equipment NOT exceeding the rated current
4. Please always check and recharge the battery before using
5. Do not open the timer under any circumstances or try to fix it by yourself

RATED CURRENT:

ALWAYS OPERATE THE TIMER WITH EQUIPMENT NOT EXCEEDING THE RATED CURRENT

Rated Current

UK 13A (220 - 240V 50Hz) / AU 10A (220 - 240V 50Hz) / EU 16A (220 - 240V 50Hz) / US 15A (110 - 120V 50Hz)